

1310nm 1x3/3x3

1x3/3x3

FBT Coupler

400-2050nm



/

		1x3	3x3
-		1x3	3x3
nm		1310	
nm		± 20	
%		1x3 33/33/33(only 3x3)	
dB		0.8	1.0
%		± 5(1x3) / ± 10(3x3)	
W		0.5 2 5	
-		SMF-28e	
-		FC/APC	
m		1	
mm		3.0x54 or 4.0x60()	
		-40 +85	
		-50 +85	

25

5dB

	Through Port	Coupling Port
40/20/40	± 5.0	± 6.0
35/30/35	± 4.0	± 5.0
33/33/33	± 6.0	± 6.0
30/40/30	± 4.0	± 3.0
25/50/25	± 3.5	± 2.4
20/60/20	± 3.3	± 2.0
15/70/15	± 3.0	± 1.8
10/80/10	± 2.8	± 1.6
5/90/5	± 2.5	± 1.5



13-1x3 33-3x3	1310-1310nm	424-40/20/40 333-33/33/33 343-30/40/30 252-25/50/25 262-20/60/20 171-15/70/15 181-10/80/10 595-5/90/5	L-0.5W 1-1W 5-5W S-	S2-SMF-28e	08-0.8m 10-1.0m 15-1.5m S-	B-250um L-900um S-	N-None FP-FC/PC FA-FC/APC S-	

MCFBT-13-1310-333-L-S2-10-L-FA

, 1x3 , 1310nm, 33: 33: 33, 500 , 4. 0x60mm
SMF-28e, 1 , 900um , FC/APC